

IO-D16A3-TO16

XL I/O Expansion Module Technical Specifications

The Unitronics® IO-D16A3-TO16 is an XL I/O expansion module for use in conjunction with specific Unitronics controllers. XL modules comprise enhanced I/O configurations and detachable I/O connectors. A local or remote I/O adapter module is required to interface between the expansion module and the PLC controller and provide power to the expansion modules in the system.

The I/O expansion module provides:

- 16 digital inputs, includes 1 HSC
- 3 analog inputs
- 16 transistor outputs, includes 1 HSO

For additional information and wiring diagrams, visit the Technical Library at www.unitronics.com.

Technical Specifications

General

Maximum current consumption	65mA (provided by the adapter 5VDC supply for I/O modules)
Status indicators	
RUN: Green LED	<ul style="list-style-type: none"> ▪ Lights when a communication link is established between the module and the PLC or remote I/O adapter ▪ Blinks when the communication link fails

Digital Inputs

Number of inputs	16 (in a single group)
Input mode	pnP (positive logic) or npN (negative logic) – configurable by hard-wiring
Galvanic isolation	None
Status indicators	
IN: Green LEDs	<ul style="list-style-type: none"> ▪ One green LED for each input: Lights when the input is active, see note 1
Nominal input voltage	24VDC
Input voltage	
pnP (positive logic)	0–5VDC for logic state 0 17–28.8VDC for logic state 1
npN (negative logic)	17–28.8VDC for logic state 0 0–5VDC for logic state 1
Input current	3.7mA @ 24VDC
Input impedance	6.5k Ω
Response time	10ms typical
High-speed input	The specifications in this section apply when an input is configured as a high-speed counter or frequency measurer. If configured as a general purpose digital input, the specification is as above. See notes 2, 3, and 4.
Resolution	16-bit or 32-bit, depending on the PLC or remote I/O adapter
Frequency	30kHz maximum (at 24VDC \pm 10%)
Minimum pulse width	14 μ s

Notes:

1. If the input is active but there is no communication with the PLC or the remote I/O adapter (RUN blinks), the status LED does not light.
2. Input 4 can function either as a high-speed counter, frequency measurer, or general purpose digital input.
3. Input 5 can function either as a counter reset input or general purpose digital input. In both cases, the specifications of this input are those of a general purpose digital input.
4. If input 4 is set as a high-speed counter and no reset input is configured, input 5 functions as a general purpose digital input.

Analog Inputs

Number of inputs	3
Input type	0–20mA or 4–20mA
Input impedance	191Ω
Maximum input rating	28mA, 5.3VDC
Galvanic isolation	None
Cable type	Shielded twisted-pair
Conversion method	Successive approximation
Resolution (0-20mA)	10-bit (1024 units)
Resolution (4-20mA)	204 to 1023 (820 units)
Conversion time	Each configured input is sampled once per 1.67ms. For example, if 3 inputs are configured, it takes $3 \times 1.67 = 5$ ms to sample all the analog inputs. See note 5.
Accuracy	±0.9% of full scale
Status indication	In software: If a specific input value is 1024, a single analog input deviates above the permissible range. If all the input values are 1024, either all the inputs deviate above the permissible range or the RG signal is not connected.

Notes:

- The conversion time does not include communication time with the PLC and PLC scan time.

Digital Outputs

Number of outputs	16 transistors	
Output type	Output 0: Either pnp: P-MOSFET (open drain) or npn: N-MOSFET (open drain) Outputs 1–15: pnp: P-MOSFET (open drain) Refer to notes 6 and 7	
Galvanic isolation	None	
Status Indicators	<ul style="list-style-type: none"> OUT: Red LEDs S.C.: Red LED <ul style="list-style-type: none"> One red LED for each output: Lights when the corresponding output is active Lights when a pnp output transistor load causes a short-circuit, see note 8 	
Maximum output current	pnp 0.5A per output, 4A total	npn 50mA
Maximum surge current	0.6A peak, once every 2 seconds, for a duration of 10ms per output, not simultaneously	N/A
Maximum delay OFF to ON	1ms	1μs
Maximum delay ON to OFF	0.15ms	10μs
HSO freq. range with resistive load	1Hz–500Hz (at max. load resistance of 470kΩ)	1Hz–32kHz (at max. load resistance of 1.5kΩ)
Maximum ON voltage drop	0.5VDC	0.4VDC
Short circuit protection	Yes	No
Voltage Reference	Digital output power supply	3.5VDC to 28.8VDC, unrelated to the voltage of either the I/O module or the controller
Output power supply		
Nominal operating voltage	24VDC	
Operating voltage	20.4VDC to 28.8VDC	

Notes:

- Output 0 can be wired either as pnp (source) or npn (sink). pnp and npn can be used simultaneously.
- Output 0 can be used as a high speed output.
- When an output load causes a short-circuit, the system disconnects that output and lights the S.C. LED on the module's front panel. The short circuit is also identified by the PLC software. For example, in the Vision OPLC, SB 5 turns on and SDW 5, containing a bitmap, indicates which module has caused the short-circuit. For more information, refer to the PLC online help.

Dimensions

Size (W x H x D)	80 x 135 x 60mm (3.15 x 5.31 x 2.36"). For exact dimensions, refer to the product installation guide.
Weight (approximate)	327g (11.5oz)

Environmental

Operating temperature	0° to 50°C (32° to 122°F)
Storage temperature	–20° to 60°C (–4° to 140°F)
Relative Humidity (RH)	10% to 95% (non-condensing)
Mounting	Snap-mounted on 35mm DIN-rail (IP20/NEMA1)

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the foregoing from the market. All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information. The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R^g) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.